

How to change the LED-Lighting on TWS Amps?

The TWS Lulis Signature Amp, as well as the TWS 2864-S Top later than SN #0016 come with an RGB-Light Strip that can be controlled via Bluetooth or WiFi directly from your smartphone. Here's your Guide to get on top of it...







3. Getting the App ready - II

Second, you will be asked if the App can connect to your Local WiFi Network.

Yes, that's OK, your Smartphone is probably already connected to it anyways... so please click "Ok".



4. Getting the App ready - III

Third, you will be asked if the App is allowed to send you notifications.

Well, it's up to you how intimate you want to be with the app. We prefer to click "Don't Allow".





4. Getting the App ready - IV

Now the App will tell you, that it is ready to connect to your amp by hitting the "+" Symbol on the upper right.

Great! That's what we're looking for.



5. Bring your TWS-Amp into "Pairing Mode" Yes, this sounds somehow odd... but this is how Bluetooth works.

With your amp being "Off" and in "Standby", do the following: Turn On and Off your amp 4 times in a sequence with a rhythm of about 1s between every switch:

On - Off - On - Off - On - Off - On

The LED-Strip in your amp should now be in "Party Mode" (= Pairing Mode), blinking in different colors, being very excited to see what will happen next.





6. Connect your TWS-Amp with the App - I

Great. Your amp is in "Pairing Mode" and your App is also ready for it. That's what we're looking for.

So hit the "+" Symbol on the upper right... and... suddenly it gets more complicated, just as in real life.

20:35		ul 🗟 🔲			
Cancel	Sign In				
Sign in with you	Sign in with your Magic Home account				
Password					
	Sign In				
	Ret	rieve Password			
Don't have an	account?				
	Register Accoun	t			
Local Model (without account)					

6. Connect your TWS-Amp with the App - II First of all, the Magic Home App wants to sell us an Account. If you

want, you can get "married" right away... you're free to do it.

But we prefer to select "Local Mode (without Account)" on the Bottom of the screen. Let's keep it a bit more casual for now.







7. Connect your TWS-Amp with the App - III

Yes "Magic Home App", we know that you're not happy that we didn't create an Account.

It's totally ok that we cannot access all features. Just hit "Confirm"...

8. Connect your TWS-Amp with the App - IV

Ok, this is getting a bit "intimate", but the App won't let us "Pair" with the Amp if we don't allow at least one time to track where we are. We recommend hitting "Allow once".

When hitting "Don't allow", the App will tell that pairing with the amp is a "NoNo" and cancel everything. We don't want that.





9. Connect your TWS-Amp with the App - V

Finally, we're so close ...

The App should discover your Amp as "Controller XXXXXX". Please select it, by clicking on it.

20:3	6					
Back	LEDnet0006B0FF0A(v3) ک				
Choose a Wi-Fi Network						
RECOMME	NDED NETWORKS					
Mario_C	DG_2GEXT	a >				
OTHER NE	TWORKS					
RAVEVA		`				
RAVEVA	L. C.	a >				
RAVEVA	RAVEVA Gastzugang					
Mario_C	Mario_OG					
AirTies_	AirTies_Air4920_D843					
Mario_C	G_2GEXT_EXT	a >				
Others	·					
If you are unable to find your network, try refreshing the list. You could also enter the network manually by selectina "Others.". Bluetooth local mode" "Bluetooth local mode" does not need to be connected to the router, only needs to be controlled by the mobile phone Bluetooth direct connection device						

10. Connect your TWS-Amp with the App - VI Woah.. WiFi Networks!

Actually, you could integrate your TWS Amp in your WiFi-Controlled Home Lighting System and control the RGB Strip together with the light on your Aquarium. But you probably don't want to get that fancy.

So, we recommend to just hit "Bluetooth Local Mode".

By doing so, you will not have your TWS Amp making friends with your Aquarium over WiFi, but just control it directly via Bluetooth.





20:36 🕣	"II 🕹 🔲
All Complete	d
You can also set a name for the de	vice
Controller B0FF0A	
DONE	
	_

11. Connect your TWS-Amp with the App - VII

Yes, Magic Home App... we know that you want us to connect via WiFi to offer your "Special Services".

F... Off! We are sure we don't want it. Please just click "YES".

12. Connect your TWS-Amp with the App - IIIX
Heureka, we made it!
Just hit "DONE"



2	20:37							
	All Completed							
You ci	an also	set a	name	for th	e dev	ice		
My T	WS Am	p						٥
				DONE				
			Dev	vice Na	ime			Done
1	amp Amps Amphitheater					leater		
qwertzuiop					p p			
а	s	d	f	g	h	j	k	I
Ŷ	У	x	с	v	b	n	m	\otimes
123	٢	space				done		
)	_				_	1	Ŷ

13. Connect your TWS-Amp with the App - IIX

Oh, and while we're already there... you can also type in a name for the RGB Lighting in your TWS Amp.

"My TWS Amp" is ok, but lacking some phantasy...

How about "My Precious" if you're into Lord of the Rings, or "The wet dream of my sleepless nights"? Get creative!

And don't forget to hit "DONE" at the end.

20.37 🖌		
20.07 V 20.07 V	Home	+
Q Device		^
My TWS / Light On, 100	Amp 0%	С
°සී° Group		^
All Device	es (1)	Ċ
		-

14. Being the "Light Jockey" - I

Booom... we're there. Finally! You're ready to go...





15. Being the "Light Jockey" - II

If you "Push & Hold" your device, you can edit its configuration.

"Rename" is a handy feature if you went a little OTT with naming your Amp or weren't creative at all.

"Change Device Type" is pretty important to let the RGB-Strip in your TWS Amp to work properly with your App.

16. Being the "Light Jockey" - III

When hitting "Change Device Type", please check that the Device in your App is configured to be "RGB & W" and has the wiring sorting "BRG W".

Note:

The TWS amps don't support "White" as an individual color. If you want your TWS Amp to be RGBW, please contact us and we will be happy to do a Custom Order for you.





11. Being the "Light Jockey" - IV

You're ready to go!

Change the color in your TWS to your liking, put it into "Mic Mode" to react to your ambience sounds, put it into "Music Mode"... etc.

You can do all crazy stuff with it. Please enjoy!